

| 型名 | 社名 | 用途 | 構造 | 端子 番号 | 最大定格 | | | | | | 電氣的特性 (Ta=25°C) | | | | | | | | | | | | |
|---------|-----|--------------|------|----------|---------|--------|-------|------|-------|---------------------------------|------------------|-----------------|------------------|------------------|------------------|-----------------|------------------|-----------------|------------------|----------------|----------------|-----------------|----------------|
| | | | | | V*** | | VGS* | | I* | P _D /P _{CH} | I _{GSS} | V _{GS} | I _{DSS} | I _{DSS} | V _{GZS} | V _{P1} | V _{GZS} | V _{P2} | V _{G1S} | g _m | g _m | V _{DS} | I _D |
| | | | | | (V) | 区分*** | (V) | 区分* | (A) | 区分* | (max)(A) | | | | | | | | | | | | |
| 3SK127 | 東芝 | UHF RF/MIX | MOS | N DE | 15 DS | ±8 0 | 30m D | 150m | ±50n | ±6 | 0 | 6m | 3 | -1.5 | 3 | -1 | 3 | | 17m | 6 | 10m | | |
| 3SK128 | 松下 | UHF LN A | MOS | N DE | 15 DS | ±8 | 30m D | 200m | ±20n | ±8 | | | | -1 | 5 | -0.5 | 1 | 8m | 12.5m | 10 | 10m | | |
| 3SK129 | 松下 | UHF RF | GaAs | N D | 13 DS | -3.5 0 | 50m D | 350m | ±20n | ±3.5 | 8.5m | 40m | 0 | -3.5 | 0 | -3.5 | 0 | 18m | 25m | 5 | 10m | | |
| 3SK131 | NEC | VHF RF/MIX | MOS | N DE | 20 DS | ±8 0 | 25m D | 200m | ±20n | ±8 | 7m | 25m | 3 | -2 | 0 | -1.5 | 0 | 22m | 28m | 6 | 10m | | |
| 3SK132 | NEC | UHF Tuner | MOS | N DE | 20 DS | ±10 0 | 25m D | 200m | ±20n | ±10 | 0.5m | 8m | 4 | -2 | 4 | -0.7 | 4 | 18m | 22m | 10 | 10m | | |
| 3SK132A | NEC | UHF Tuner | MOS | N DE | 20 DS | ±8 0 | 25m D | 200m | ±20n | ±8 | 0.5m | 8m | 4 | -2 | 4 | -0.7 | 4 | 18m | 22m | 5 | 10m | | |
| 3SK133 | NEC | UHF TV Tuner | MOS | N DE | 20 DS | ±10 0 | 25m D | 200m | ±20n | ±10 | 0.01m | 6m | 4 | -2 | 4 | -0.7 | 4 | 14m | 17m | 10 | 10m | | |
| 3SK133A | NEC | UHF TV Tuner | MOS | N DE | 20 DS | ±8 0 | 25m D | 200m | ±20n | ±8 | 0.01m | 6m | 4 | -2 | 4 | -0.7 | 4 | 14m | 17m | 5 | 10m | | |
| 3SK134 | NEC | UHF RF | MOS | N | 15 DS | ±8 0 | 25m D | 200m | ±20n | ±8 | | | | -2 | 4 | -0.7 | 4 | 24m | 27.5m | 10 | 10m | | |
| 3SK134A | NEC | UHF Tuner | MOS | N DE | 18 DSX | ±8 | 25m D | 200m | ±20 | ±8 | 0.5m | 8m | -2 | -2 | -4 | -0.7 | -4 | 24m | 27.5m | 5 | 10m | | |
| 3SK135 | NEC | UHF RF | MOS | N | 18 DS | ±10 0 | 25m D | 200m | ±20n | ±8 | 0.01m | 6m | 4 | -2 | 4 | -0.7 | 4 | 14m | 18m | 10 | 10m | | |
| 3SK135A | NEC | UHF TV Tuner | MOS | N DE | 20 DS | ±8 0 | 25m D | 200m | ±20n | ±8 | 0.01m | 6m | 4 | -2 | 4 | -0.7 | 4 | 14m | 18m | 5 | 10m | | |
| 3SK136 | 日立 | VHF TV Tuner | MOS | N DE | 20 DS | ±8 0 | 35m D | 150m | ±100n | ±8 | 5m | 25m | 4 | -3 | 4 | -2 | 0 | 8m | | 15 | 10m | | |
| 3SK137 | 日立 | UHF TV Tuner | MOS | N DE | 15 DS | ±10 0 | 35m D | 150m | ±100n | ±8 | | 20m | 3 | -2 | 3 | -2 | 3 | 14m | | 6 | 10m | | |
| 3SK137V | 日立 | VHF TV Tuner | MOS | N DE | 15 DS | ±10 | 35m D | 150m | ±100n | ±8 | | 20m | 3 | -2 | 3 | -2 | 3 | 14m | | 6 | 10m | | |
| 3SK138 | 日立 | UHF TV Tuner | MOS | N DE | 15 DS | ±10 0 | 35m D | 150m | ±100n | ±8 | | 10m | 3 | -1 | 3 | -1 | 3 | 10m | 15m | 6 | 10m | | |
| 3SK139 | 松下 | U/VHF LN A | MOS | N DE | 15 DS | ±8 | 30m D | 150m | ±20n | ±8 | 1m | 11m | 4 | -3 | 4 | -1.5 | 0 | 12m | 20m | 10 | 10m | | |
| 3SK140 | 東芝 | UHF RF/MIX | GaAs | N D | 10 DS | -6 0 | 50m D | 150m | -20 μ | -5 | 20m | 45m | 0 | -4 | 0 | -4 | 0 | | 17m | 5 | 10m | | |
| 3SK141 | 松下 | UHF RF | GaAs | N D | 13 DS | -3.5 0 | 50m D | 200m | ±20n | ±3.5 | 8.5m | 40m | 0 | -3.5 | 0 | -3.5 | 0 | 18m | 25m | 5 | 10m | | |
| 3SK142 | 松下 | UHF LN A | MOS | N DE | 15 DS | ±8 | 30m D | 250m | ±20n | ±8 | 0.5m | 13m | 4 | -3 | 4 | -1 | 0 | 12m | 20m | 10 | 10m | | |
| 3SK143 | 松下 | UHF LN A | MOS | N DE | 15 DS | ±8 | 30m D | 200m | ±20n | ±8 | 0.2m | 13m | 4 | -3 | 4 | -1 | 0 | 12m | 20m | 10 | 10m | | |
| 3SK144 | 松下 | VHF LN A | MOS | N DE | 15 DS | ±8 | 30m D | 150m | ±20n | ±8 | 0.8m | 15m | 4 | -3 | 4 | -3 | 4 | 17m | 23m | 10 | 10m | | |
| 3SK145 | 東芝 | UHF RF/MIX | MOS | N DE | 13.5 DS | ±8 0 | 30m D | 200m | ±50n | ±6 | 0 | 6m | 3 | -1.5 | 3 | -1 | 3 | | 16m | 6 | 10m | | |
| 3SK146 | 東芝 | UHF RF/MIX | MOS | N DE | 13.5 DS | ±8 0 | 30m D | 150m | ±50n | ±6 | 0 | 6m | 3 | -1.5 | 3 | -1 | 3 | | 16m | 6 | 10m | | |
| 3SK150 | 東芝 | UHF RF/MIX | MOS | N DE | 15 DS | ±8 0 | 30m D | 200m | ±50n | ±6 | 3m | 14m | 3 | -1.5 | 3 | -1 | 0 | 22m | 27m | 6 | 10m | | |
| 3SK151 | 東芝 | VHF RF/MIX | MOS | N DE | 15 DS | ±8 0 | 30m D | 150m | ±50n | ±6 | 3m | 14m | 3 | -1.5 | 3 | -1 | 0 | 22m | 27m | 6 | 10m | | |
| 3SK152 | 東芝 | V/UHF RF | MOS | N DE | 13.5 DS | ±8 0 | 30m D | 200m | ±50n | ±6 | 0 | 6m | 3 | -1.5 | 3 | -1 | 3 | | 21m | 6 | 10m | | |
| 3SK153 | 東芝 | V/UHF RF | MOS | N DE | 13.5 DS | ±8 0 | 30m D | 150m | ±50n | ±6 | 0 | 6m | 3 | -1.5 | 3 | -1 | 3 | | 21m | 6 | 10m | | |
| 3SK154 | 日立 | VHF TV Tuner | MOS | N DE | 15 DSX | ±8 | 35m D | 150m | ±100n | ±8 | | 30m | 3 | -2 | 3 | -2 | 3 | 15m | | 6 | 10m | | |
| 3SK156 | 日立 | UHF TV Tuner | MOS | N DE | 12 DS | ±8 0 | 35m D | 200m | ±50 μ | ±5 | 0 | 12m | 3 | -1.7 | 3 | -1.4 | 3 | 14m | | 6 | 10m | | |

| 電 気 的 特 性 (Ta=25℃) | | | | | | | | | | | コンブリ メンタリ | 外形 | 備 考 | 型 名 | |
|----------------------|----------------------|------------------------|------------------------|-----------|-----------|-----------|-----------------------|-------------------------------------|------------------------|-----------------------|--------------------------------|--------------|------|--------|-----------|
| Cis (typ) (pF) | Crs (typ) (pF) | V _{GS} (V) | V _{DS} (V) | NF typ | NF max | f (Hz) | R _G (Ω) | R _{DS(ON)} (max) (Ω) | V _{GS} (V) | I _D (A) | | | | | そ の 他 特 性 |
| 2 | 0.03max | 3 | 6 | 3.2 | | 800M | | | | | PG=16dBtyp | f=800MHz | 176 | G1G2DS | 3SK127 |
| 1.7 | 0.02 | -5 | 10 | 1.9 | 3.3 | 800M | | | | | PG=10dBmin/14dBtyp | f=800MHz | 147C | DSG2G1 | 3SK128 |
| 0.6 | 0.02 | -3.5 | 5 | 1.2 | 2 | 1G | | | | | PG=17dBtyp | f=1GHz | 91B | DSG2G1 | 3SK129 |
| 5 | 0.05 | 3 | 6 | 1.3 | 2.5 | 200M | | | | | PG=24dBtyp | f=200MHz | 177 | SDG2G1 | 3SK131 |
| 2.5 | 0.02 | 4 | 10 | 3.8 | 5.5 | 900M | | | | | PG=18dBtyp | f=900MHz | 177 | SDG2G1 | 3SK132 |
| 2.5 | 0.02 | 4 | 10 | 2.8 | 4.5 | 900M | | | | | PG=22dBtyp | f=900MHz | 177 | SDG2G1 | 3SK132A |
| 2 | 0.02 | 4 | 10 | 3.8 | 5.5 | 900M | | | | | PG=16dBtyp | f=900MHz | 177 | SDG2G1 | 3SK133 |
| 2 | 0.02 | 4 | 10 | 3.0 | 5.0 | 900M | | | | | PG=17dBtyp | f=900MHz | 177 | SDG2G1 | 3SK133A |
| 2.5 | 0.02 | 4 | 10 | 2.4 | 4.5 | 900M | | | | | PG=22.5dBtyp | f=900MHz | 177 | SDG2G1 | 3SK134 |
| 2.5 | 0.02 | 0 | 10 | 2.4 | 4.5 | 900M | | | | | PG=23dBtyp | f=900MHz | 177 | SDG2G1 | 3SK134A |
| 1.9 | 0.02 | 4 | 10 | 2.8 | 4.5 | 900M | | | | | PG=17dBtyp | f=900MHz | 177 | SDG2G1 | 3SK135 |
| | 0.02 | 4 | 10 | 2.7 | 4.5 | 900M | | | | | PG=18dBtyp | f=900MHz | 177 | SDG2G1 | 3SK135A |
| 5 | 0.03 | 4 | 15 | 3.3 | 200M | | | | | | PG=17dBmin | f=200MHz | 178 | SDG2G1 | 3SK136 |
| 2.6 | 0.02 | 3 | 6 | | 5 | 900M | | | | | PG=10dBmin | f=900MHz | 178 | SDG2G1 | 3SK137 |
| 2.6 | 0.02 | 3 | 6 | | 3.0 | 200M | | | | | PG=20dBmin | f=200MHz | 199A | SG1G2D | 3SK137V |
| 2 | 0.02 | 3 | 6 | | 5 | 900M | | | | | PG=10dBmin | f=900MHz | 178 | SDG2G1 | 3SK138 |
| 2.3 | 0.02 | -5 | 10 | 2.8 | 4.5 | 500M | | | | | PG=24/15dBtyp | f=200/500MHz | 147B | SDG2G1 | 3SK139 |
| 0.9 | 0.02 | 0 | 5 | 1.5 | 2.5 | 800M | | | | | PG=20.5dBtyp | f=800MHz | 176 | G1G2DS | 3SK140 |
| 0.6 | 0.02 | -3.5 | 5 | 1.2 | 2 | 1G | | | | | PG=17dBtyp | f=1GHz | 147B | SDG2G1 | 3SK141 |
| 1.9 | 0.02 | -5 | 10 | 3.5 | 4.5 | 800M | | | | | PG=11.5dBmin/14dBtyp | f=800MHz | 139C | SDG1G2 | 3SK142 |
| 1.9 | 0.02 | -5 | 10 | | 5 | 800M | | | | | PG=13dBmin/15dBtyp | f=800MHz | 147B | SDG2G1 | 3SK143 |
| 3.8 | 0.02 | -5 | 10 | 2 | 3.2 | 200M | | | | | PG=23dBtyp | f=50/200MHz | 147B | SDG2G1 | 3SK144 |
| 1.8 | 0.02 | 3 | 6 | 2.6 | 4 | 800M | | | | | PG=17.5dBtyp | f=800MHz | 125A | G1SDG2 | 3SK145 |
| 1.8 | 0.02 | 3 | 6 | 2.6 | 4 | 800M | | | | | PG=17.5dBtyp | f=800MHz | 176 | G1G2DS | 3SK146 |
| 2.7 | 0.025 | 3 | 6 | | 5.5 | 200M | | | | | 変換利得G _{cs} =24.5dBtyp | f=200/245MHz | 125A | G1SDG2 | 3SK150 |
| 2.7 | 0.025 | 3 | 6 | | 5.5 | 200M | | | | | 変換利得G _{cs} =24.5dBtyp | f=200/245MHz | 176 | G1G2DS | 3SK151 |
| 2.7 | 0.025 | 3 | 6 | 2.6 | 4 | 800M | | | | | PG=18.5dBtyp | f=800MHz | 125A | G1SDG2 | 3SK152 |
| 2.7 | 0.025 | 3 | 6 | 2.6 | 4 | 800M | | | | | PG=18.5dBtyp | f=800MHz | 176 | G1G2DS | 3SK153 |
| 4.5 | 0.03 | 3 | 6 | | 3 | 200M | | | | | PG=22dBmin | f=200MHz | 199A | SG1G2D | 3SK154 |
| 4.7 | 0.03 | 3 | 6 | 2.2 | 3 | 200M | | | | | PG=23dBtyp | f=200MHz | 175A | G1G2DS | 3SK156 |